

## LifeBook T3010

- Designed for Microsoft® Windows® XP Tablet PC Edition
- Seamless Wi-Fi connectivity
- 12.1" XGA TFT active digitiser
- 2GB maximum memory support
- Programmable security features



Fujitsu recommends Microsoft® Windows® XP Tablet PC Edition for Mobile Computing.

| T3010 Specifications          |  |
|-------------------------------|--|
| <b>Processor</b>              | Intel® Centrino™ Mobile Technology<br>- Intel® Pentium® M Processor 1.40GHz<br>- Intel® PRO/Wireless 2200BG (802.11b/g) <sup>3</sup> / 2100BG (802.11b/g) network connection with Dual Antenna<br>- Intel® 855GM Chipset |
| <b>OS Supported</b>           | Microsoft® Windows® XP Tablet PC Edition   |
| <b>Secondary Cache</b>        | 1MB  |
| <b>Memory</b>                 | 256MB SDRAM, Max. 2GB (DDR266)   |
| <b>Hard Disk Drive</b>        | 40GB (Ultra DMA/100 and S.M.A.R.T. support)  |
| <b>Display</b>                | 12.1" XGA TFT Colour (Max 1024x768 dots)   |
| <b>LCD Type</b>               | Transmissive   |
| <b>Digitizer</b>              | Electromagnetic (Active)   |
| <b>Graphics</b>               | Integrated Intel® Extreme Graphics 2, with maximum 64MB shared memory. DVMT <sup>1</sup> delivers low-power, high-performance 2D/3D graphics, video, and display capabilities  |
| <b>Sound</b>                  | AC Link Audio (AC97 compliance: RealTek ALC202) with Internal Speaker, Internal Microphone   |
| <b>Communication</b>          | V.90 Modem & 100/10Mbps LAN  |
| <b>External I/O Interface</b> | 1 x VGA, 2 x USB 2.0, 1 x RJ11, 1 x RJ45,<br>Audio (Headphone-out, Microphone-in), Docking for Port Replicator, AC Adapter Power Input   |
| <b>Quick Touch Panel</b>      | Application Mode:<br>Application Launch Buttons and 2 programmable buttons<br>Security Mode:<br>Anti-Theft Lock with 800,000 possible password combinations  |
| <b>Security</b>               | BIOS Lock, Hard Disk Lock & Smart Card support   |
| <b>Keyboard</b>               | 82-key w/19mm key pitch, 3mm key stroke  |
| <b>Pointing Device</b>        | Touch Pad with Scroll Button   |
| <b>Card Slot</b>              | PC Card Slot Type I/II x 2   |
| <b>IR Interface</b>           | IrDA 1.1 (Max. 4Mbps)  |
| <b>AC Adapter</b>             | Input: AC100-240V, Output: DC16V 60W   |
| <b>Battery</b>                | Approx. 4.4hrs <sup>2</sup> , Lithium-Ion  |
| <b>Other Software Bundled</b> | Norman Virus Control & Norman Personal FireWall  |
| <b>Dimensions</b>             | 293mm(W) x 236mm(D) x 27.4mm min.(H)   |
| <b>Weight</b>                 | Approx. 1.9kg  |

<sup>1</sup> Dynamic Video Memory Technology (DVMT) dynamically responds to application requirement and efficiently allocates the proper amount of memory (max. 64MB) for optimal and graphics performance. The memory size available to the Operating System will be less than the total size of installed memory modules.

<sup>2</sup> Results obtained from Ziff Davis (BusinessWinstone 2001) Battery Mark V1.0.1

Actual battery life will vary based on screen brightness, applications, features, power management settings, battery conditioning, and other customer preferences. DVD or hard drive usage may also have a significant impact on battery life.

<sup>3</sup> Configurations varies amongst countries. Please check actual configuration with your local distributors.

It is natural for all thin-film transistor (TFT) liquid crystal displays (LCD) to show a small number of missing or discoloured dots. These are commonly known as non-conforming pixels. This is a technology limitation of TFT LCD and does not represent a defect. Fujitsu warranty does not cover limitations in technology such as non-conforming pixels.

Specifications reflected above are engineering and hardware specifications. They do not represent actual usage or operating dimensions, sizes, performances and weights as these are dependent on factors such as operating temperature, type of operating system and application used, connected devices and accessories as well as hardware configurations of the notebook.

**SINGAPORE:**  
Fujitsu PC Asia  
Pacific Pte Ltd  
Tel : (65) 6776 0688  
Fax : (65) 6776 0788

**MALAYSIA:**  
Fujitsu PC Asia  
Pacific Pte Ltd  
Tel : (60-3) 2093 3997  
Fax : (60-3) 2093 4245

**HONG KONG:**  
Fujitsu PC  
Asia Pacific Ltd  
Tel : (852) 3101 8133  
Fax : (852) 3101 0633

**THAILAND:**  
Fujitsu Systems  
Business (Thailand) Ltd  
PC Division  
Tel : (66-2) 263 7888  
Fax : (66-2) 263 7880  
www.fujitsu-pcap.in.th

**AUSTRALIA:**  
Fujitsu PC Australia  
Toll Free: 1800 288 283  
Tel : (61-2) 9004 7455  
Fax : (61-2) 9004 7720  
www.lifebook.com.au

**CHINA:**  
Fujitsu PC China  
Division  
Tel : (86-21) 3310 0808  
Fax : (86-21) 3310 0606  
www.pc-cn.fujitsu.com

**PHILIPPINES:**  
Fujitsu Philippines Inc.  
Tel : (63-2) 812 4001  
Fax : (63-2) 817 7576

**TAIWAN:**  
Fujitsu Taiwan Ltd  
Tel : (886-2) 2311 2255  
Fax : (886-2) 2311 2277

**VIETNAM:**  
Fujitsu Vietnam Ltd  
Tel : (84-4) 831 3895-7  
Fax : (84-4) 831 3898

**INDONESIA:**  
PT Fujitsu Systems  
(Indonesia)  
Tel : (62-21) 344 2601  
Fax : (62-21) 344 2593

Note: For countries not listed above, please contact our Singapore office.



experience  
the evolution

All rights to the mentioned trademarks reside with their respective owners. Fujitsu endeavours to ensure that the information in this documentation is correct and fairly stated, but does not accept liability for any errors or omissions. The development of Fujitsu products and services is continuous and published information may not be up to date. It is important to check the current position with Fujitsu. The document is not part of the contract or licence save in so far as may be expressly agreed.

Dealer: